

◎ 订货举例

系列代码	—		螺纹大小	牙型代码
A	M5: M5	20: 3/4"	P: PT	
V	06: 1/8"	25: 1"	G: G	
VF	08: 1/4"	32: 1-1/4"	T: NPT	
...	10: 3/8"	40: 1-1/2"		
	15: 1/2"	50: 2"		

订货举例: A系列消声器, 接管口径为G1/8", G牙, 其ERP编码为: A-06G


◎ 消声器

A型消声器	型号	螺纹大小	S
	A-M5	M5	9
	A-06	1/8"	13
	A-08	1/4"	17
	A-10	3/8"	22
	A-15	1/2"	24
	A-20	3/4"	30
	A-25	1"	36
	A-32	1 1/4"	46
	A-40	1 1/2"	52
	A-50	2"	64

V型消声器	型号	螺纹大小	S
	V-M5	M5	8
	V-06	1/8"	12
	V-08	1/4"	15
	V-10	3/8"	19
	V-15	1/2"	22
	V-20	3/4"	30
	V-25	1"	36

VF型消声器	型号	螺纹大小	S
	VF-M5	M5	8
	VF-06	1/8"	13
	VF-08	1/4"	16
	VF-10	3/8"	19
	VF-15	1/2"	24

◎ 消声排气节流阀

SB型消声排气节流阀	型号	螺纹大小	S
	SB-06	1/8"	12
	SB-08	1/4"	14
	SB-10	3/8"	17
	SB-15	1/2"	24
	SB-20	3/4"	27
	SB-25	1"	34

SD型消声排气节流阀	型号	螺纹大小	S
	SD-06	1/8"	12
	SD-08	1/4"	15
	SD-10	3/8"	19
	SD-15	1/2"	22
	SD-20	3/4"	27
	SD-25	1"	34

SPK型消声排气节流阀	型号	螺纹大小	S
	SPK-06	1/8"	10
	SPK-08	1/4"	14
	SPK-10	3/8"	17
	SPK-15	1/2"	24
	SPK-20	3/4"	30
	SPK-25	1"	36



◎ 塑料消声器 PT牙、NPT牙不能订购

PSU型消声器 (桔盖黑体)	型号	螺纹大小	S
	PSU-M5	M5	7
	PSU-06	1/8"	13
	PSU-08	1/4"	17
	PSU-10	3/8"	25
	PSU-15	1/2"	25
	PSU-20	3/4"	37
	PSU-25	1"	48

PSE型消声器	型号	螺纹大小	S
	PSE-M5	M5	7
	PSE-06	1/8"	13
	PSE-08	1/4"	17
	PSE-10	3/8"	25
	PSE-15	1/2"	25
	PSE-20	3/4"	37
	PSE-25	1"	48

带快速接头型消声器	型号	适用管径	L
	EXAN-C06	6	46.5
	EXAN-C08	8	46
	EXAN-C10	10	56.5
	EXAN-C12	12	83

◎ 管塞

管塞	型号	D	B	C	P1	P2	外形尺寸图
	EPP04	4	28	15	5	3	
	EPP06	6	31.8	17	7	4.3	
	EPP08	8	35.7	18	8.9	3.9	
	EPP10	10	42	20	11	5	
	EPP12	12	44	23	13	6	
	EPP14	14	46.6	24.5	13.5	6.6	
	EPP16	16	45.7	24.5	15.4	8.7	

1

气动控制元件

2

流体控制元件

3

电气控制元件

4

气动执行元件

5

气源处理元件

6

真空元件

7

洁净元件

8

高真空元件

9

气动辅助元件